O Special Considerations for Data from Older Telescopes in $\mathcal{AIPS}$

Chapter 4 on data calibration has been revised to describe the modern VLA data format and calibration in $\mathcal{AIPS}$. Similarly, old VLBI formats have been excised from Chapter 9 to avoid confusion with more modern practices. Nonetheless, the VLA archive for the pre-expansion VLA is widely and productively used and we suspect that there are VLBI users with older data files which may still need reduction and analysis. This appendix is used to address first the older VLA data format and initial reduction steps and then the older Mk III and Mk IV VLBI formats.

O.1 The Historical VLA

The NRAO archive contains all of the data from the historical (or pre-EVLA) Very Large Array. These data are frequently mined for uses above and beyond those of the original observers. There is a new archive at `https://data.nrao.edu`; the old archive is no longer available. Log in at the above web address using your `my.nrao.edu` account and then select Show Search Inputs. This has all sorts of ways to find what you may desire. You may specify one or more of telescope, project code, date range, target name, target coordinates and search radius, observing band, or telescope configuration. You may submit your query and the tool will show you all data sets that match your specification. You may then request the data sets that you actually want and they will be downloaded to a publicly accessible disk area. All historical VLA data have been in the public domain for a long time, so no special permission should be needed. You will be notified when your data are available and told how to access them.

The old archive contained less well known content which is not available in the new archive. Instead the web site `https:www.vla.nrao.edu/astro/nvas/` describes an archive of $\mathcal{AIPS}$-processed legacy VLA data sets containing calibrated data and images. There is a description of this service and, at the left, buttons to connect to various web pages of informations and also a search tool.

For VLA data from the archive, use `FILLM` to read one or more disk files; see § O.1.1. The VLA format was changed on January 1, 1988, but all older data were translated and archived in the modern format. On July 1, 2007, the ModComps were replaced with modern computers and the format had an essential change made to it. Use `FILLM` to read data from both the ModComp and post-ModComp eras.

For VLA calibration, there are several useful procedures described in this chapter and Chapter 4. They are contained in the `RUN` file called `VLAPROCS`. Each of these procedures has an associated `HELP` file and inputs. Before any of these procedures can be used, this `RUN` file must be invoked with:

> RUN VLAPROCS $^{C}_{R}$ to compile the procedures.

There is a "pipeline" procedure designed to do a preliminary calibration and imaging of ordinary VLA data sets. This provides a good first look at the data. Nonetheless, the results are still not likely to be of publishable quality. To run the pipeline, enter

> RUN VLARUN $^{C}_{R}$ to compile the procedures.

> INP VLARUN $^{C}_{R}$ to review the input adverbs and, when ready,

> VLARUN $^{C}_{R}$ to execute the pipeline.

See Appendix A for a simplified summary of data reduction suitable to data from the historic VLA. Much of the calibration of historic VLA data is similar to that of the modern EVLA, although the latter is fundamentally multi-channel and wide band. See Chapter 4 for a discussion of the steps used in calibrating

all VLA data.

O.1.1 Reading from VLA archive files using FILLM

The NRAO Archive makes available, among other things, data from the EVLA, which began observing in January 2010, and from the old VLA which ceased observing a few days into 2010. To load data from the EVLA into *AIPS* consult Chapter 4 for information about BDF2AIPS and other options. The following describes how to read old VLA data into *AIPS*.

The Archive now serves VLA data in the form of one or more "MOdComp" format disk files. To load these into *AIPS*, enter

> TASK 'FILLM' ; INP ↵	to review the inputs needed.
> DATAIN 'MYDATA:AC238_' ↵	to read from the disk area pointed at by the logical MYDATA and the data from program ID AC238.
> NFILES 0 ↵	to start with file AC238_1. If your first file is *e.g.*, AC238_4, set NFILES = 3.
> NCOUNT 3 ↵	to read three data files AC238_1 through AC238_3.
> OUTNA ' ' ↵	to take the default output file name.
> OUTDI 3 ↵	to write the data to disk 3 (one with enough space).
> DOUVCOMP -1 ↵	to write visibilities in uncompressed format. VLA files are small by modern standards, so saving space is not worth the costs.
> DOWEIGHT 1 ↵	Data weights will depend on the "nominal sensitivity" and should be calibrated along with the visibility amplitudes (DOCALIB = 1).
> CPARM 0 ↵	to do no averaging of the data in FILLM.
> CPARM(6) 1 ↵	to select VLA sub-array 1.
> CPARM(7) 2000 ↵	to have observations within 2 MHz be regarded as being at the same frequency.
> CPARM(8) 1 ↵	to use a 1-minute interval for the CL table; default is 5 min.
> CPARM(9) 0.25 ↵	to use a 15-second interval for the TY table; default is the input data interval.
> DPARM 0 ↵	to have no selection by specific frequency.
> REFDATE '*yyyymmdd*' ↵	to specify the year, month, and day of the reference date. This should be the first date in the data set (or earlier). All times in *AIPS* will be measured with respect to that date and must be positive. The default is the first date included by the data selection adverbs, which may not be the desired one. Note that REFDATE is only a reference point; it does not affect which data are loaded from the the files.
> TIMERANG *db* , *hb* , *mb* , *sb* , *de*, *he* , *me* , *se* ↵	to specify the beginning day, hour, minute, and second and ending day, hour, minute, and second (wrt REFDATE) of the data to be included. The default is to include all times.
> INP ↵	to review the inputs.
> GO ↵	to run the program when you're satisfied with inputs.

In 31DEC21, FILLM first tries to open the file under the name in DATAIN. If that fails, it then tries the name in DATAIN with the file number appended as described above.

There are numerous adverbs including BAND, QUAL, CALCODE, VLAOBS. and VLAMODE to limit what data were loaded from magnetic tapes which could hold data from multiple projects. These adverbs still function, but are of little use today. Note that the values given above are illustrative and should not be copied verbatim in most cases.

Be careful when choosing the averaging time with CPARM(1). If you have a large data set, setting this time too *low* will make an unnecessarily large output file; this may waste disk space and slow the execution of subsequent programs. Setting it too *high* can, however, (1) smear bad data into good, limiting the ability to recognize and precisely remove bad data, (2) smear features of the image that are far from the phase center, and (3) limit the dynamic range that can be obtained using self-calibration. If you need a different (usually shorter) averaging time for the calibrator sources than for your program sources, use CPARM(10) to specify the averaging time for calibrators. See Lectures 12 and 13 in *Synthesis Imaging in Radio Astronomy*[1] for general guidance about the choice of averaging time given the size of the required field of view and the observing bandwidth.

CPARM(2) controls a number of mostly esoteric options. If your data include the Sun (see § O.1.8) or planets, you must set CPARM(2) = 16 to avoid having each scan on the moving source assigned a different name. The adverb DOWEIGHT = 1 has the same affect as CPARM(2) = 8 and both select the use of the nominal sensitivity to scale the data weights. When this is done, the weights will be $1/\sigma^2$ as they should for imaging, with σ in "Jy" in the same uncalibrated scale as the fringe visibilities. Having selected this option, you should apply any amplitude calibration to the weights as well as the visibilities. If you store the data in compressed form, only one weight may be retained with each sample. Any differences between polarizations and/or IFs in that sample will be lost. Uncompressed data require less CPU, but more real, to read but 2 to 3 times as much disk space to store.

CPARM(2)=2048 allows you to load data as correlation coefficients, which can be scaled to visibilities later with TYAPL (§ O.1.3). CPARM(3) controls which on-line flags are applied by FILLM, which now always writes an OF table containing information about these flags. That information can be viewed with PRTOF and applied selectively to the data at a later time with OFLAG.

FILLM writes a weather (WX) table to the output file. At the same time, it uses "canned" VLA antenna gain curves and a balance of the current with a seasonal model weather data to estimate opacity and gain corrections to be written into the first calibration (CL) table. These functions are controlled by adverbs CALIN and BPARM and may be turned off, although the default is to make the corrections. In subsequent tasks, set DOCALIB = 1 to use these initial calibration data. If, for some reason, the data weights do not depend on the nominal sensitivity, use DOCALIB=100 to apply calibration.

Where possible, FILLM will try to place all data in one file. However, in many cases this is not possible. For instance so-called "channel 0" data from a spectral-line observation will be placed in a separate file from its associated line data. Similarly, scans which have differing numbers of frequency channels will also be placed into separate files. Another case is observations made in mode LP, *i.e.*, one IF-pair is set to L band, the other to P band. In this case the two bands will be split into separate files. Yet another case arises when there are observations of different bandwidths. All of this should be relatively transparent to the user.

FILLM and many *AIPS* tasks are able to handle multiple, logically different, frequencies within a multi-source data set. FILLM does this by assigning an FQ number to each observation and associating a line of information about that frequency in the FQ file associated with the data set. Users should note that this concept can become quite complicated and that not all tasks can handle it in full generality. In fact, most tasks can only process one FQ number at a time. Polarization calibration works only on one FQ at a time since the antenna file format allows for only one set of instrumental polarization parameters. Therefore, it is *strongly* advised that you fill continuum experiments which involve multiple frequencies into separate data sets. FILLM will separate bands automatically, but you will have to force any remaining separation. To

[1] *Synthesis Imaging in Radio Astronomy*, Astronomical Society of the Pacific Conference Series, Volume 6 "A Collection of Lectures from the Third NRAO Synthesis Imaging Summer School" eds. R. A. Perley, F. R. Schwab and A. H. Bridle (1989)

do this, (a) use the QUAL adverb in FILLM, assuming that you have used separate qualifiers in OBSERVE for each frequency pair; (b) use the DPARM adverb array in FILLM to specify the desired frequencies precisely; or (c) use the UVCOP task to separate a multiple FQ data set into its constituent parts. Note that the first two options require multiple executions of FILLM, while the third option requires more disk space.

Spectral-line users and continuum observers using different frequencies in the same band should be aware of the FQ entry tolerance. Each frequency in a *uv* file will be assigned an FQ number as it is read from disk by FILLM. For spectral-line users, the observing frequency will normally change as a function of time due to Doppler tracking of the Earth's rotation, or switching between sources or between spectral lines; in general, this will cause different scans to have different FQ numbers. FILLM assigns an FQ number to a scan based on the FQ tolerance adverb CPARM(7) which defines the maximum change of frequency allowed before a new FQ number is allocated. If CPARM(7) < 0, the the same FQ number is assigned to all data in spectral-line data sets. If CPARM(7) is positive, a scan's will be assigned to an existing FQ number if

$$\|\nu_{current} - \nu_{firstFQ}\| < \mathtt{CPARM}(7)$$

where $\nu_{firstFQ}$ is the frequency of the first sample to which the particular FQ number was assigned. If no match is found, then a new FQ number is created and assigned and another line added to the FQ table file. Alternatively, if CPARM(7) is zero, then the FQ tolerance is assumed to be half of the maximum frequency difference caused by observing in directions 180 degrees apart (*i.e.*, $\Delta\nu = 10^{-4} \times \nu$).

An example: if an observer observes the 1612, 1665 and 1667 MHz OH masers in VY CMa and NML Cygnus, then presumably he would like his data to have 3 FQ numbers, one associated with each OH transition. However, running FILLM with CPARM(7) set to 0 would produce 6 FQ numbers because the frequency difference between the masers in VY CMa and NML Cygnus is greater than the calculated tolerance of 160 kHz. Therefore, in order to ensure that only 3 FQ numbers are assigned, he should set CPARM(7) to 1000 kHz. Setting CPARM(7) < 0 would result in all data having the same FQ number, which is clearly undesirable.

For most continuum experiments the FQ number will be constant throughout the database. Normally any change in frequency should be given a new FQ number. To achieve this, FILLM treats CPARM(7) differently for continuum. If CPARM(7) $\leq$ 0.0, then FILLM assumes a value of 100 kHz. A positive value of CPARM(7) is treated as a tolerance in kHz as in the spectral line case.

Note: *If your uv database contains several frequency identifiers, you should go through the calibration steps for each* FQ *code separately.*

FILLM can still read from magnetic tape. Set DATAIN to blanks, mount your tape (adverb INTAPE), index the tape with PRTTP, and use the adverbs to limit the data loaded to that portion of your project in which you are interested.

If FILLM is executing correctly, your message terminal will report the number of your observing program, the VLA archive format revision number, and then the names of the sources as they are found in the data files. Once FILLM has completed, you can find the database on disk using:

> INDI 0 ; UCAT C_R

This should produce a listing such as:

```
Catalog on disk  3
Cat Usid Mapname      Class  Seq  Pt     Last access      Stat
  1  103 25/11/88    .X BAND.   1 UV 26-JAN-2018 12:34:16
```

You might then examine the header information for the disk data set by:

> INDI 3 ; GETN 1 ; IMHEAD C_R

This should produce a listing like:

```
AIPS 1: Image=MULTI     (UV)         Filename=25/11/88    .X BAND.   1
AIPS 1: Telescope=VLA                Receiver=VLA
AIPS 1: Observer=AC238               User #=   36
AIPS 1: Observ. date=25-NOV-1988     Map date=26-JAN-2018
AIPS 1: # visibilities   2613887     Sort order  TB
AIPS 1: Rand axes: UU-L-SIN  VV-L-SIN  WW-L-SIN  BASELINE  TIME1
AIPS 1:            SOURCE  FREQSEL
AIPS 1: ----------------------------------------------------------------
AIPS 1: Type    Pixels   Coord value     at Pixel     Coord incr   Rotat
AIPS 1: COMPLEX      1   1.0000000E+00       1.00  1.0000000E+00    0.00
AIPS 1: STOKES       4  -1.0000000E+00       1.00 -1.0000000E+00    0.00
AIPS 1: FREQ         1   8.4110000E+09       1.00  1.2500000E+07    0.00
AIPS 1: IF           2   1.0000000E+00       1.00  1.0000000E+00    0.00
AIPS 1: RA           1    00 00 00.000       1.00       3600.000    0.00
AIPS 1: DEC          1    00 00 00.000       1.00       3600.000    0.00
AIPS 1: ----------------------------------------------------------------
AIPS 1: Coordinate equinox 1950.00
AIPS 1: Maximum version number of extension files of type HI is   1
AIPS 1: Maximum version number of extension files of type AN is   1
AIPS 1: Maximum version number of extension files of type NX is   1
AIPS 1: Maximum version number of extension files of type SU is   1
AIPS 1: Maximum version number of extension files of type FQ is   1
AIPS 1: Maximum version number of extension files of type CL is   1
AIPS 1: Maximum version number of extension files of type TY is   1
AIPS 1: Maximum version number of extension files of type WX is   1
AIPS 1: Maximum version number of extension files of type OF is   1
AIPS 1: Keyword = 'CORRMODE'  value = '        '
AIPS 1: Keyword = 'VLAIFS  '  value = 'ABCD    '
AIPS 1: Keyword = 'CORRCOEF'  value =           -1
```

This header identifies the file as a multi-source file (`Image=MULTI`) with 2613887 floating-point visibilities in time-baseline (`TB`) order. There are two entries on the `IF` axis. These correspond to the old VLA's "AC" and "BD" IF-pairs respectively. The description of the frequency (`FREQ`) axis shows that the first IF ("AC") is at 8411 MHz and has 12.5 MHz bandwidth. The parameters of the second IF-pair ("BD") are determined from the data in the `FQ` table file and cannot be read directly from this header; these values are shown in the `'SCAN'` listing from `LISTR`. The header shown above indicates that the data are in compressed format since the number of pixels on the `COMPLEX` axis is 1 and the `WEIGHT` and `SCALE` random parameters are not present. Uncompressed data does not use these random parameters and has 3 pixels on the `COMPLEX` axis.

The term "IF" can be confusing. At the VLA, IFs "A" and "C" correspond to right-hand and left-hand circularly polarized (RHC and LHC) signals, respectively, and are normally for the same frequency in an observing band. Such pairs, if at the same frequency, are considered to be one "IF" in *AIPS*. An observation which was made in spectral line mode "`2AC`" is considered at the VLA to have two "IFs" whereas within *AIPS* this would be filled as one "IF" with two polarizations if they were both observed with the same frequency, the same number of channels, and the same channel separation. If these conditions do not hold, then they are filled into separate *uv* files, each with a single IF and a single polarization. The term "sub-array" is also confusing. At the VLA — and in task `FILLM` — sub-array means the subset of the 27 antennas actually used to observe your sources. (The historic VLA allowed up to 5 simultaneous sub-arrays in this sense.) In the rest of *AIPS*, sub-array refers to sets of antennas used together at the same time. If observations from separate times (*e.g.*, separate array configurations) are concatenated into the same file, then *AIPS* will regard the separate sets of antennas as different "sub-arrays" whether or not the same physical antennas occur within more than one of these sub-arrays.

Besides the main *uv* data file, this header listing shows that there are numerous "extension" files attached to the data. These are, in order, the history, antenna, index, source, frequency, calibration, system temperature,

weather, and on-line flags tables. LISTR with OPTYPE='SCAN' provides a useful summary of the index, source, and frequency tables.

If your experiment contains data from several bands FILLM will place the data from each band in separate data sets. Also, if you observed with several sets of frequencies or bandwidths in a given observing run these will be assigned different FQ numbers by FILLM. You can determine which frequencies correspond to which FQ numbers from the 'SCAN' listing provided by LISTR. Line data are divided into the "channel 0" (central $3/4$ of the of the observing band averaged) and the spectra. Data observed in the "LP" mode (or any other two-band mode) will be broken into separate data sets, one for each band.

O.1.2 Reading old spectral-line data

If your spectral-line data are in a VLA archive disk file, they should be read into *AIPS* using FILLM, as described in §O.1.1. FILLM will fill a typical line observation into two files, a large one containing the line data only, and a smaller file containing the "channel-0" data. (Note that FILLM computes channel-0 from the line data rather than using the channel-0 provided by the on-line system.) The standard calibration and editing steps are performed on channel 0 and the results copied over to the line data set. *You must be careful with the tolerance you allow* FILLM *to use in determining the* FQ *numbers. If you desire all of your data to have the same* FQ *number, so that you can calibrate it all in one pass, then set* CPARM(7) *in* FILLM *to an appropriately large value.* If you wish to retain spectral-line autocorrelation data, you must set DOACOR to true.

By default for the VLA, the channel-0 data are generated by the vector average of the central *3/4* of the observing band. If this algorithm is not appropriate for your data, you may generate your own channel-0 data set by averaging only selected channels. You may now select different spectral channels in different IFs. To do this, use the task AVSPC:

> TASK 'AVSPC' $^{C}_{R}$	
> INDI n ; GETN m $^{C}_{R}$	to specify line data set.
> OUTDI i ; OUTCL 'CH 0' $^{C}_{R}$	to specify output "channel-0" data set disk and class.
> ICHANSEL 10, 30, 1, 0, 31, 55, 2, 1 $^{C}_{R}$	for example, to average every channel between 10 and 30 in all IFs and also every other channel between 31 and 55, but only in IF 1.
> GO $^{C}_{R}$	to create a new channel-0 data set.

You might find this necessary when observing neutral hydrogen at galactic velocities. Most calibrator sources have some absorption features at these frequencies.

O.1.3 Applying nominal sensitivities to historic VLA data

FILLM scales the correlation coefficients by the instantaneous measured "nominal sensitivities," producing data approximately in deci-Jy. The VLA nominal sensitivities are stored in the TY table as "system temperatures" (T_{sys}). For calibration purposes, it is best to have the nominal sensitivities applied, but it may be better to use a clipped and/or time-smoothed version of those sensitivities. If you want to do this, load the T_{sys} data into the TY table with the highest time resolution possible by setting CPARM(9)=0 in FILLM. FILLM can also be told not to apply the nominal sensitivities and therefor produce correlation coefficients by setting CPARM(2)=2048, but this is not strictly necessary. In order to smooth and clip the TY table use the task TYSMO. If you have done editing such as QUACK, it may help to copy the data with UVCOP, applying your flag table not only to the visibilities but also to the TY table (UVCOPPRM(6)=3) before running TYSMO to remove questionable values at the start of scans. Alternatively, SNEDT will apply the data flags to the table allowing you to write a new, cleaned-up version of the table. Then a TY table may be applied (and/or removed) from a data set with TYAPL:

> TASK 'TYAPL' ; INP C$_R$	to review the inputs needed.
> INDI n ; GETN m C$_R$	to select the correct data set.
> FREQID 1 C$_R$	to select FQ number 1.
> INVERS 1 C$_R$	TY table to remove from data, will only work if data are not already correlation coefficients.
> IN2VERS 2 C$_R$	smoothed TY table to apply to data, will only work if data is in correlation coefficient form — either initially or after removal of INVERS.
> INP C$_R$	to re-check *all* the inputs parameters.
> GO C$_R$	to start the task.

O.1.4 Calibrating historic VLA data

There are many similarities to the calibration of historic and modern VLA data. After reading in the data, you should with both run LISTR for the scan listing, PRTAN for the antenna layout information, and VLANT to correct antenna positions; see § 4.2.2 and § 4.3.1 for details. The general discussion on flagging (§ 4.3.10) applies to both types of data. However, with historic VLA data one does a purely continuum calibration and editing initially. If the observation is of spectral lines, the flag and calibration tables are copied to the line uv data file following the calibration of "channel 0." Thus, the spectral editing tasks such as SPFLG, FTFLG, and RFLAG become useful only in the second half of spectral-line reductions. TVFLG (§ O.1.6 below) is the preferred interactive editing task and editing with LISTR plus UVFLG (§ O.1.5 below) is actually a reasonable option.

O.1.5 Editing with LISTR and UVFLG

Data may be flagged using task UVFLG based on listings from LISTR. To print out the scalar-averaged raw amplitude data for the calibrators, and their *rms* values, once per scan in a matrix format, the following inputs are suggested:

> TASK 'LISTR' ; INP C$_R$	to review the inputs needed.
> INDI n; GETN m C$_R$	to select the data set, $n = 3$ and $m = 1$ above.
> SOURCES ' ' ; CALCODE '*' C$_R$	to select calibrators.
> TIMER 0 C$_R$	to select all times.
> ANTENNAS 0 C$_R$	to list data for all antennas.
> OPTYPE 'MATX' C$_R$	to select matrix listing format.
> DOCRT FALSE C$_R$	to route the output to printer, not terminal.
> DPARM 3 , 1 , 0 C$_R$	amplitude and *rms*, scalar scan averaging.
> BIF 1; EIF 0 C$_R$	to select all IFs, LISTR will list IFs separately.
> FREQID 1 C$_R$	to select FQ number 1 (note that FQ numbers must also be done separately).
> INP C$_R$	to review the inputs.
> GO C$_R$	to run the program when inputs set correctly.

For unresolved calibrators, the VLA on-line gain settings normally produce roughly the same values in all rows and columns within each matrix. At L, C, X, and U bands, these values should be approximately 0.1 of the expected source flux densities. At P band, the factor is about 0.01. The factors for other bands are unspecified. Any rows or columns with consistently high or low values in either the amplitude or the *rms* matrices should be noted, as they probably indicate flaky antennas. In particular, you should look for

- In the amp-scalar averages, look for *dead* antennas, which are easily visible as rows or columns with small numbers. Rows or columns that differ by factors of two or so from the others are generally fine. Such deviations mean only that the on-line gains were not set entirely correctly.
- In the *rms* listings, look for discrepant high values. Almost all problems are antenna based and will be seen as a row or column. Factors of 2 too high are normally okay, while factors of 5 high are almost certainly indicative of serious trouble.

The next step is to locate the bad data more precisely. Suppose that you have found a bad row for antenna 3 in right circular polarization in IF 2 between times (*d1*, *h1*, *m1*, *s1*) and (*d2*, *h2*, *m2*, *s2*). You might then rerun LISTR with the following new inputs:

> SOURCES '' C_R	to select all sources.
> TIMER *d1 h1 m1 s1 d2 h2 m2 s2* C_R	to select by time range.
> ANTENNAS 1 , 2 , 3 C_R	to list data for antenna 3 with two "control" antennas.
> BASEL 1 , 2 , 3 C_R	to list all baselines with these three antennas.
> OPTYPE 'LIST' C_R	to select column listing format.
> DOCRT 1 C_R	to route the output to terminal at its width.
> DPARM = 0 C_R	amplitude only, no averaging.
> STOKES 'RR' C_R	to select right circular.
> BIF 2 C_R	to specify the "BD" IFs.
> FLAGVER 1 C_R	to choose flag table 1.
> GO C_R	to run the program.

This produces a column listing on your terminal of the amplitude for baselines 1–2, 1–3 and 2–3 at every time stamp between the specified start and stop times. The '1–2" column provides a control for comparison with the two columns containing the suspicious antenna.

Note that "amp-scalar" averaging ignores phase entirely and is therefore not useful on weak sources, nor can it find jumps or other problems with the phases. To examine the data in a phase-sensitive way, repeat the above process, but set DPARM(2) = 0 rather than 1. Bad phases will show up as reduced amplitudes and increased *rms*'s.

Once bad data have been identified, they can be expunged using UVFLG. For example, if antenna 3 RR was bad for the full interval shown above, it could be deleted with

> TASK 'UVFLG' ; INP C_R	to select the editor and check its inputs.
> TIMER *d1 h1 m1 s1 d2 h2 m2 s2* C_R	to select by time range.
> BIF 2 ; EIF = BIF C_R	to specify the "BD" IFs.
> BCHAN 0 ; ECHAN 0 C_R	to flag all channels.
> FREQID 1 C_R	to flag only the present FQ number.
> ANTEN 3 , 0 C_R	to select antenna 3.
> BASEL 0 C_R	to select all baselines to antenna 3.
> STOKES 'RR' C_R	to select only the RR Stokes (LL was found to be okay in this example).
> REASON = 'BAD RMS WHOLE SCAN' C_R	to set a reason.
> OUTFGVER 1 C_R	to select the first (only) flag table.
> INP C_R	be careful with the inputs here!
> GO C_R	to run the task when ready.

Continue the process until you have looked at all parts of the data set that seemed anomalous in the first matrix listing, then rerun that listing to be sure that the flagging has cleaned up the data set sufficiently. If

there are lots of bad data, you may find that you have missed a few on the first pass. If you change your mind about a flagging entry, you can use UVFLG with OPCODE = 'UFLG' to remove entries from the flag table. All adverbs of UVFLG are used when removing entries, so you may use REASON along with the channel, IF, source, et al. adverbs to select the entries to be removed. OPCODEs 'REAS' and 'WILD' may be used to undo an entry solely based on the REASON. If the table becomes hopelessly messed up, use EXTDEST to delete the flag table and start over or use a higher numbered flag table. The contents of the flag table may be examined at any time with the general task PRTAB and entries in it may also be removed with TABED and/or TAFLG. Two flag tables can be merged using TAPPE.

O.1.6 Editing with TVFLG

If your data are seriously corrupted, contain numerous baselines, and you like video games, TVFLG is the visibility editor of choice. The following discussion assumes that you have read § 2.3.2 and are familiar with using the *AIPS* TV display. The following inputs are suggested:

> TASK 'TVFLG' ; INP C$_R$	to review the inputs needed.
> INDI n ; GETN m C$_R$	to select the data set, $n = 3$ and $m = 1$ above.
> SOURCES ' ' C$_R$	to select all sources.
> TIMER 0 C$_R$	to select all times.
> STOKES 'FULL' C$_R$	to select all four or 'HALF' to select the two parallel-hand polarizations; you can then toggle between them interactively.
> FREQID 3 C$_R$	Select FQ entry 3.
> BIF 1 ; EIF 2 C$_R$	to specify both VLA IFs; you can then toggle between the two interactively.
> ANTENNAS 0 C$_R$	to display data for all antennas.
> BASELINE 0 C$_R$	to display data for all baselines.
> DOCALIB 1 C$_R$	to apply initial calibration to the data.
> FLAGVER 1 C$_R$	to use flag (FG) table 1.
> OUTFGVER 0 C$_R$	to create a new flag table with the flags from FG table 1 plus the new flags.
> DPARM = 0 C$_R$	to use default initial displays and normal baseline ordering.
> DPARM(6) = 30 C$_R$	to declare that the input data are 30-second averages, or to have the data averaged to 30 seconds. Note that one can interactively increase the time averaging, in integer units of DPARM(6), after the master grid is created.
> DPARM(5) = 10 C$_R$	to expand the flagging time ranges by 10 seconds in each direction. The times in the master grid are average times and may not encompass the times of the samples entering the average without this expansion.
> DOCAT 1 C$_R$	to save the master grid file.
> INP C$_R$	to review the inputs.
> GO C$_R$	to run the program when inputs set correctly.

If you make multiple runs of TVFLG, it is important to make sure that the flagging table entries are all in one version of the FG table. The easiest way to ensure this is to set FLAGVER and OUTFGVER to 0 and keep it that way for all runs of TVFLG. If you make a mistake, two flag tables may be merged with the task TAPPE.

TVFLG begins by constructing a "master grid" file of all included data. This can be a long process if you include lots of data at once, even though a faster, large-memory method of gridding is now usually used. It is probably better to use the channel selection (including averaging channels with NCHAV), IF selection,

source selection, and time range selection adverbs to build rather smaller master grid files and then to run TVFLG multiple times. It will work with all data included, allowing you to select interactively which data to edit at any one moment and allowing you to resume the editing as often as you like. But certain operations (such as undoing flags) have to read and process the entire grid, and will be slow if that grid is large. The master grid file is always cataloged (on IN2DISK with class TVFLGR), but is saved at the end of your session only if you set DOCAT = 1 (actually > 0) before starting the task. To resume TVFLG with a pre-existing master grid file, set the adverb IN2SEQ (and IN2DISK) to point at it. When resuming in this way, TVFLG ignores all of its data selection adverbs since they might result in a different master grid than the one it is going to use. If you wish to change any of the data selection parameters, *e.g.*, channels, IFs, sources, times, or time averaging, then you must use a new master grid.

Kept with the master grid file is a special file of TVFLG flagging commands. This file is updated as soon as you enter a new flagging command, making the master grid and your long editing time virtually proof from power failures and other abrupt program terminations. These flagging commands are not entered into your actual *uv* data set's flagging (FG) table until you exit from TVFLG and tell it to do so. During editing, TVFLG does not delete data from its master grid; it just marks the flagged data so that they will not be displayed. This allows you to undo editing as needed during your TVFLG session(s). When the flags are transferred to the main *uv* data set, however, the flagged data in the master grid are fully deleted since undoing the flags at that point has no further meaning. When you are done with a master grid file, be sure to delete it (with ZAP) since it is likely to occupy a significant amount of disk.

TVFLG keeps track of the source name associated with each row of data. When averaging to build the master grid and to build the displayed grids, TVFLG will not average data from different sources and will inform you that it has omitted data if it has had to do so for this reason. For multi-source files, the source name is displayed during the CURVALUE-like sections. However, the flagging table is prepared to flag *all* sources for the specified antennas, times, *etc.* or just the displayed source. If you are flagging two calibrator scans, you may wish to do all sources in between as well. Use the SWITCH SOURCE FLAG interactive option to make your selection before you create flagging commands. Similarly, you will need to decide whether flagging commands that you are about to prepare apply only to the displayed channel and/or IF, or to all possible channels and/or IFs. In particular, spectral-line observers often use TVFLG on the pseudo-continuum "channel-0" data set, but want the resulting flags to apply to all spectral channels when copied to the spectral-line data set. They should be careful to select all channels before generating any flagging commands. Each flagging command generated is applied to a list of Stokes parameters, which *does not have to include* the Stokes currently being displayed. When you begin TVFLG and whenever you switch displayed Stokes, you should use the ENTER STOKES FLAG option to select which Stokes are to be flagged by subsequent flagging commands.

If you get some of this wrong, you can use the UNDO FLAGS option in TVFLG if the flags have not yet been applied to the *uv* data set. Or you can use tasks UVFLG, TABED or TAFLG to correct errors written into the FG table of your multi-source *uv* data set. Flag tables are now used with both single- and multi-source data sets.

TVFLG displays the data, for a single IF, channel (average), and Stokes, as a grey-scale display with time increasing up the screen and baseline number increasing to the right. Thus baselines for the VLA run from left to right as 1–1, 1–2, 1–3, ..., 2–2, 2–3, ..., 27–27, 27–28, and 28–28. An input parameter (DPARM(3) = 1 allows you to create a master grid and display baselines both as, say 1–2 and 2–1. An interactive (switchable) option allows you to order the baselines from shortest to longest (ignoring projection effects) along the horizontal axis.

The interactive session is driven by a menu which is displayed on a graphics overlay of the TV display. An example of this full display is shown on the next page. Move the cursor to the desired operation (noting that the currently selected one is highlighted in a different color on many TVs) and press button A, B, or C to select the desired operation; pressing button D produces on-line help for the selected operation. The first (left-most column) of choices is:

OFFZOOM	turn off any zoom magnification
OFFTRANS	turn off any black & white enhancement
OFFCOLOR	turn off any pseudo-coloring
TVFIDDLE	interactive zoom, black & and white enhancement, and pseudo-color contours as in AIPS
TVTRANSF	black & white enhancement as in AIPS
TVPSEUDO	many pseudo-colorings as in AIPS
DO WEDGE ?	switches choice of displaying a step wedge
LOAD xxxx	switch TV load transfer function to xxxx
LIST FLAGS	list selected range of flag commands
UNDO FLAGS	remove flags by number from the FC table master grid
REDO FLAGS	re-apply all remaining flags to master grid
SET REASON	set reason to be attached to flagging commands
DO LABEL ?	turn axis labeling on and off

Note: when a flag is undone, all cells in the master grid which were first flagged by that command are restored to use. Flag commands done after the one that was undone may also, however, have applied to some of those cells. To check this and correct any improperly un-flagged pixels, use the REDO FLAGS option. This option even re-does CLIP operations! After an UNDO or REDO FLAGS operation, the TV is automatically re-loaded if needed. Note that the UNDO operation is one that reads and writes the full master grid.

The load to the TV for all non-phase displays may be done with all standard transfer functions: LINear, LOG, SQRT, LOG2 (more extreme log). The menu shows the next one in the list (xxxx above) through which you may cycle. The TV is reloaded immediately when a new transfer function is selected.

Column 2 offers type-in controls of the TV display and controls of which data are to be flagged. In general, the master grid will be too large to display on the TV screen in its entirety. The program begins by loading every $n^{\rm th}$ baseline and time smoothing by m time intervals in order to fit the full image on the screen. However, you may select a sub-window in order to see the data in more detail. You may also control the range of intensities displayed (like the adverb PIXRANGE in TVLOD inside AIPS). The averaging time to smooth the data for the TV display may be chosen, as may the averaging time for the "scan average" used in some of the displays. Which correlators are to be flagged by the next flagging command may be typed in. All of the standard Stokes values, plus any 4-bit mask may be entered. The spectral channel and IF may be typed in. Flagging may be done only for the current channel and IF and source, or it may be done for all channels and/or IFs and/or sources. Note that these controls affect the next LOADs to the TV or the flagging commands prepared after the parameter is changed. When the menu of options is displayed at the top of the TV, the current selections are shown along the bottom. If some will change on the next load, they are shown with a trailing asterisk. Column 2 contains

ENTER BLC	Type in a bottom left corner pixel number on the terminal
ENTER TRC	Type in a top right corner pixel number on the terminal
ENTER AMP PIXRANGE	Type in the intensity range to be used for loading amplitude images to the TV
ENTER PHS PIXRANGE	Type in the phase range to be used for loading phase images to the TV
ENTER RMS PIXRANGE	Type in the intensity range to be used for loading images of the rms to the TV
ENTER R/M PIXRANGE	Type in the value range to be used for loading rms/mean images to the TV
ENTER SMOOTH TIME	Type in the time smoothing (averaging) length in units of the master grid cell size



Figure O.1: A display of a sample TV screen from TVFLG, made using the *AIPS* task TVCPS to produce a negative black-and-white display. The TVFLG menu (in the boxes) is displayed in a graphics plane which is normally colored light green. The status line(s) at the bottom and optional axis labels are displayed in a graphics plane that is normally cyan in color. The data are grey scales in a TV memory and may be enhanced in black-and-white or pseudo-colored. The particular display chosen is the amplitude of the vector difference between the sample and a running vector average of samples surrounding it. This particular parameter is sensitive to both phase and amplitude problems and may save you the extra time of looking at phase and amplitude separately. It requires that there be data to average, but does not blur the flagging by the averaging interval (as the RMS method does). The visibility data are from the JVLA. All baselines are shown once only in baseline number order. Antenna 8 and 27 are missing for all times, while antennas 11 and 22 are missing for some times in the piece displayed here. The displayed data are the RR Stokes samples and have been windowed to exclude some times. Flag commands generated at the moment illustrated will flag all source names, one spectral channel (actually channels 9-24 averaged here), one IF, and Stokes RR only (from a 2-Stokes data set). The step wedge and labeling options have been selected.

ENTER SCAN TIME	Type in the time averaging length for the "scan average" in units of the master grid cell size
ENTER CHANNEL	Type in the desired spectral channel number using the terminal
ENTER IF	Type in, on the terminal, the desired IF number
ENTER STOKES FLAG	To type in the 4-character string which will control which correlators (polarizations) are flagged. Note: this will apply only to subsequent flagging commands. It should be changed whenever a different Stokes is displayed.
SWITCH SOURCE FLAG	To switch between having all sources flagged by the current flag commands and having only those sources included in this execution of `TVFLG` flagged. The former is desirable when a time range encompasses all of 2 calibrator scans.
SWITCH ALL-CH FLAG	To reverse the flag all channel status; applies to subsequent flag commands
SWITCH ALL-IF FLAG	To cycle the flag all IFs status; applies to subsequent flag commands

The all-channel flag remains true if the input data set has only one channel and the all-IF flag remains true if the input data set has no more than one IF. If there are more than 2 IFs, the `SWITCH ALL-IF FLAG` cycles between flagging one IF, flagging a range of IFs, and flagging all IFs. When going to the range of IFs, it will ask you to enter the desired range.

An extra word should be said about the "scan average" to which reference was made above. This is used solely for displaying the difference of the data at time T and the average of the data at times near T. This average is computed with a "rolling buffer." Thus, for a scan average time of 30 seconds and data at 10-second intervals, the average for a set of 7 points is as follows:

```
time        average of times
 00           00   10   20
 10           00   10   20
 20           10   20   30
 30           20   30   40
 40           30   40   50
 50           40   50   60
 60           40   50   60
```

The third column of options is used to control which data are displayed and to cause the TV display to be updated. The master grid must be converted from complex to amplitude, phase, the rms of the amplitude, or the rms divided by the mean of the amplitude for display. It may also be converted to the amplitude of the vector difference between the current observation and the "scan average" as defined above or the absolute value of the difference in amplitude with the scalar-average amplitude or the absolute value of the difference in phase with the vector scan average. Furthermore, the baselines may be reordered in the TV display by their length rather than their numerical position. This column has the options:

DISPLAY AMPLITUDE	To display amplitudes on the TV
DISPLAY PHASE	To display phases on the TV
DISPLAY RMS	To display amplitude rms on the TV
DISPLAY RMS/MEAN	To display amplitude rms/mean on the TV
DISPLAY VECT RMS	To display vector amplitude rms on the TV
DISPLAY VRMS/VAVG	To display vector amplitude rms/mean on the TV
DISPLAY AMP V DIFF	To display the amplitude of the difference between the data and a running (vector) "scan average"

DISPLAY AMPL DIFF	To display the abs(difference) of the amplitude of the data and a running scalar average of the amplitudes in the "scan"
DISPLAY PHASE DIFF	To display the abs(difference) of the phase of the data and the phase of a running (vector) "scan average"
DISPLAY STOKES *xx*	To switch to Stokes type *xx* (where *xx* can be RR, LL, RL, LR, etc. as chosen by the STOKES adverb).
SORT BY *xxxxxxxx*	To switch to a display with the *x* axis (baseline) sorted by ordered by LENGTH or by BASELINE number
OFF WINDOW + LOAD	Reset the window to the full image and reload the TV
SET WINDOW + LOAD	Interactive window setting (like TVWINDOW) followed by reloading the TV
LOAD LAST PIECE	Reload the TV with the previous piece of the total time range.
LOAD NEXT PIECE	Reload the TV with the next piece of the total time range.
LOAD	Reload TV with the current parameters

SET WINDOW + LOAD is "smarter" than TVWINDOW and will not let you set a window larger than the basic image. Therefore, if you wish to include all pixels on some axis, move the TV cursor outside the image in that direction. The selected window will be shown. When there are more times than will fit on the TV screen at the current smoothing (averaging) time, the task divides the data up into overlapping time-range "pieces." When it has done so, the LOAD LAST PIECE and LOAD NEXT PIECE menu items will appear. This lets you view one piece after the next, rotating through all pieces, to edit each time interval at full resolution. Note that a FLAG BASELINE will flag that baseline through all pieces.

The fourth column is used to select the type of flagging to be done. During flagging, a TV graphics plane is used to display the current pixel much like CURVALUE in AIPS. Buttons A and B do the flagging (except A switches corners for the area and time-range modes). Button C also does the flagging, but the program then returns to the main menu rather than prompting for more flagging selections. Button D exits back to the menu without doing any additional flagging. Another graphics plane is used to show the current area/time/baseline being flagged. All flagging commands can create zero, one, two, or more entries in the flagging list; hit button D at any time. There are also two clipping modes, an interactive one and one in which the user enters the clip limits from the terminal. In both, the current image computed for the TV (with user-set windows and data type, but not any other windows or alternate pixels etc. required to fit the image on the TV) is examined for pixels which fall outside the allowed intensity range. Flagging commands are prepared and the master file blanked for all such pixels. In the interactive mode, buttons A and B switch between setting the lower and upper clip limits, button C causes the clipping to occur followed by a return to the main menu, and button D exits to the menu with no flagging. The options are

FLAG PIXEL	To flag single pixels
FLAG/CONFIRM	To flag single pixels, but request a yes or no on the terminal before proceeding
FLAG AREA	To flag a rectangular area in baseline-time
FLAG TIME RANGE	To flag all baselines for a range of times
FLAG ANTENNA-DT	To flag all baselines to a specific antenna for a range of times
FLAG A TIME	To flag all baselines for a specific time
FLAG BASELINE	To flag all times for a specific baseline
FLAG BASELINE-DT	To flag a time range for a specific baseline
CLIP BY SET #S	To enter from the terminal a clipping range for the current mode and then clip high and low samples
CLIP INTERACTIV	To enter with the cursor and LUTs a clipping range for the current mode and then clip data outside the range.
CLIP BY FORM	To clip selected channels/IFs using the "method" and clipping range of some previous clip operation

LOAD NEXT IF/ST	Load TV with the next IF or polarization.
LOAD NEXT CHAN	To load the next spectral channel to the TV with current parameters
LOAD PREV CHAN	To load the previous spectral channel to the TV with current parameters

The `CLIP BY FORM` operation allows you to apply a clipping method already used on one channel/IF to other channels and/or IFs. It asks for a command number (use `LIST FLAGS` to find it) and applies its display type (amp, phase, rms, rms/mean, differences), averaging and scan intervals and clip levels to a range of channels, IFs and Stokes (as entered from the terminal). To terminate the operation, doing nothing, enter a letter instead of one of the requested channel or IF numbers. To omit a Stokes, reply, if requested for a flag pattern, with a blank line. You may watch the operation being carried out on the TV as it proceeds.

The right-most column has only the option:

EXIT	Resume `AIPS` and, optionally, enter the flags in the data

Before the flags are entered in the data, `TVFLG` asks you whether or not you actually wish to do this. You must respond yes or no. Note that, if the master grid is to remain cataloged, there is no need to enter the flagging commands every time you decide to exit the program for a while. In fact, if you do not enter the commands, you can still undo them later, giving you a reason not to enter them in the main *uv* data set too hastily.

The two most useful data modes for editing are probably amplitude and amplitude of the vector difference. The former is useful for spotting bad data over longer time intervals, such as whole scans. The latter is excellent for detecting short excursions from the norm. For editing uncalibrated data, rms of two time intervals is useful, but the rms modes require data to be averaged (inside `TVFLG`) and therefore reduce the time resolution accuracy of the flagging. If you edit by phase, consider using the pseudo-coloration scheme that is circular in color (option `TVPSEUDO` followed by button B) since your phases are also circular.

Using `TVFLG` on a workstation requires you to plan the real estate of your screen. We suggest that you place your message server window and your input window side-by-side at the bottom of the screen. Then put the TV window above them, occupying the upper 70–90% of the screen area. (Use your window manager's tools to move and stretch the TV window to fill this area.) Instructions and informative, warning and error messages will appear in the message server window. Prompts for data entry (and your data entry) appear in the input window. Remember to move the workstation cursor into the input window to enter data (such as IF, channel, antenna numbers, and the like) and then to move the cursor back into the TV area to select options, mark regions to be flagged, adjust enhancements, and so on.

O.1.7 Spectral-line calibration

The calibration of spectral-line data is very similar to that of continuum data with the exception that the antenna gains have to be determined and corrected as a function of frequency as well as time. The model used by *AIPS* is to determine the antenna gains as a function of time using a pseudo-continuum ("channel-0") form of the data. Then the complex spectral response function ("bandpass") is determined from observations of one or more strong continuum sources at or near the same frequency as the line observation. In general, the channel-0 data are calibrated using the recipes in the previous sections of this chapter. The sub-sections below are designed to bring out the few areas in which spectral-line calibration differs from continuum.

O.1.7.1 Spectral-line aspects of SETJY

The LISTR output with OPTYPE = 'SCAN' will show information from the source table including spectral-line parameters. VLA data from FILLM are normally supplied with adequate information regarding the source velocity, line rest frequency, and velocity reference (radio versus optical, LSR versus barycentric). However, data from the EVLA and other telescopes may be missing these parameters. SETJY must then be used to fill in the needed values. An OPTYPE='VCAL' option computes the velocity of the reference channel from first principles. It is recommended over inaccurate guesses of adverb values in other SETJY OPTYPEs. It may be run over all sources after the rest frequencies and velocity reference information has been filled in.

O.1.7.2 Editing the spectral data

You should follow the steps outlined in § 4.3.5 to edit the calibrator data using the channel-0 data set. Even though channel-0 data is continuum, be careful to have TVFLG and UVFLG generate the flagging commands for all channels, not just channel 1. Then, copy the resulting FG table to the line file. Use TACOP:

> TASK 'TACOP' ⏎
> INDI *n* ; GETN *m* ⏎ to specify channel-0 data set.
> OUTDI *i* ; GETO *j* ⏎ to specify the line data set.
> INEXT 'FG' ⏎ to copy the FG table.
> INVER 1 ⏎ to copy table 1.
> NCOUNT 1 ⏎ to copy only one table.
> OUTVER 1 ⏎ to copy it to output table 1
> INP ⏎ to review the inputs.
> GO ⏎ to run the program when inputs set correctly.

Specifying the "ALL-CH" setting in TVFLG and specifying BCHAN 1 ; ECHAN 0 ⏎ in UVFLG cause all channels to be flagged when the FG table is copied to the line data set.

Spectral-line observers should also use SPFLG (§ 10.2.2) to examine and, perhaps, to edit their data. This task is very similar to TVFLG described in § O.1.6, but SPFLG displays spectral channels for all IFs on the horizontal axis, one baseline at a time. If you have a large number of baselines, as with the VLA, then you should examine a few of the baselines to check for interference, absorption (or emission) in your calibrator sources, and other frequency-dependent effects. Use the ANTENNAS and BASELINE adverbs to limit the displays to a few short spacings and one or two longer ones as well. If there are serious frequency-dependent effects in your calibrators, use SPFLG and UVFLG to delete them. (You might wish to delete the FG table with EXTDEST to begin all over again.) Then use AVSPC to build a new channel-0 data set and repeat the continuum editing. Note that you should not copy the FG table from the spectral-line data set to the new continuum one. The reason for this is the confusion over the term "channel." If you have flagged channel 1, but not all channels, in the spectral-line data set — a very common occurrence — then a copied FG table would flag all of the continuum data since it has only one "channel." When you have flagged the channel-0 data set, you can merge the new flags back into the spectral-line FG table with task TABED.

> TASK 'TABED' ⏎
> INDI *n* ; GETN *m* ⏎ to specify channel-0 data set.
> OUTDI *i* ; GETO *j* ⏎ to specify the line data set.
> INEXT 'FG' ⏎ to copy the FG table.
> INVER 1 ⏎ to copy table 1.
> OUTVER 1 ⏎ to copy it to output table 1.
> BCOUNT 1 ; ECOUNT 0 ⏎ to copy from the beginning to the end.

> OPTYPE 'COPY' C_R	to do a simple copy appending the input table to the output table.
> TIMER 0 C_R	to copy all times.
> INP C_R	to review the inputs.
> GO C_R	to run the program when inputs set correctly.

If the channel-0 data set is meaningful for your program sources, you might consider doing a first-pass editing of them along with your calibrators before copying the FG table back to the line data set. If your program sources contain significant continuum emission, then this is a reasonable operation to perform. If they do not, then the standard channel-0 data set is not useful for editing program sources. You can use SPFLG to edit all channels, or if the signal is strong in a few channels, you could run TVFLG on those channels from the spectral-line data set or average those with the BCHAN, ECHAN, and NCHAV adverbs.

O.1.7.3 Calibrating the spectral data

The channel-0 data set should be calibrated as described above for continuum data (§ 4.3.5 and § 4.3.10). When you are satisfied with your results, you should copy the relevant CL table over to the line data set with TACOP:

> TASK 'TACOP' C_R	
> INDI *n* ; GETN *m* C_R	to specify the channel-0 data set.
> OUTDI *i* ; GETO *j* C_R	to specify the line data set.
> INEXT 'CL' C_R	to copy a CL table.
> INVER 0 C_R	to copy highest numbered table from CLCAL step.
> NCOUNT 1 C_R	to copy only one table.
> OUTVER 0 C_R	to create new output table.
> INP C_R	to review the inputs.
> GO C_R	to run the program when inputs set correctly.

If you copy SN, TY, or SY tables, you may apply a flagging table to the table values.

Then one runs BPASS on the bandpass calibration source(s). This is the same process as for the modern VLA; see § 4.3.8 for details.

At this point it is often useful to examine your fully calibrated data using POSSM:

> TASK 'POSSM' C_R	
> INDI *i* ; GETN *j* C_R	specify line data.
> SOURCES '*source1*' , ' ' C_R	to specify the source of interest.
> ANTENNAS 0 C_R	to plot all antennas.
> BCHAN 10 ; ECHAN 55 C_R	to plot spectrum for this channel range only.
> DOCALIB 1 C_R	to apply the antenna gain to both visibilities and weights (if appropriate). calibration.
> GAINUSE 0 C_R	to use most recent CL table.
> DOBAND 3 C_R	to apply the bandpass calibration time smoothed.
> BPVER 1 C_R	to use BP table 1.
> FREQID 1 C_R	to use only one FQ value.
> APARM 0 C_R	to do vector averaging of amplitudes and self-scale the plots.

> SMOOTH 5 , 0 C_R	to apply Hanning smoothing in the spectral domain after bandpass calibration is applied. Use 13,0 to smooth after the data are averaged, which is faster and less prone to oddities due to channel-dependent flagging. Use 1,0 only if the data were Hanning smoothed when BPASS was run.
> INP C_R	to review the inputs.
> GO C_R	to run the program when inputs set correctly.
> GO LWPLA C_R	to send the plot to the (PostScript) printer/plotter.

If you have multiple FQ entries in your data set, you should repeat the calibration for each additional FQ entry. Bookkeeping is simplified if you eliminate all extant SN tables before calibrating the data associated with each frequency identifier. However, it is not essential to do this.

O.1.8 Solar data calibration for the historic VLA

The calibration of solar *uv* data differs from normal continuum and spectral-line calibration in one critical respect: the system temperature correction to the visibility data is applied by the observer in *AIPS*. See Lecture 21 in *Synthesis Imaging in Radio Astronomy* for a discussion of the system temperature correction as it applies to VLA solar visibility data. The system temperature correction is embodied in a quantity referred to as the "nominal sensitivity," an antenna-based numerical factor normally applied in real time to the scaled correlation coefficients before they are written to the VLA archive. With the exception of X and L band, only a handful of VLA antennas are equipped with so-called "solar CALs." The nominal sensitivity is only computed for those antennas so-equipped, namely (for the old VLA) antennas 5, 11, 12, and 18 (at K, U,and C bands) and antennas 7, 12, 21, and 27 (at P band). The system-temperature correction for those antennas without solar CALs must, therefore, be bootstrapped from those antennas which do have solar CALS. This is accomplished through two tasks for the old VLA and two other tasks for the new VLA.. For the old VLA, FILLM fills the uncalibrated visibility data to disk and places the nominal sensitivities in a TY extension table. Then, SOLCL applies the nominal sensitivities to calibration parameters in the CL table. For the new VLA, BDF2AIPS reads the data in, writing a SysPower (SY) and CalDevice (CD) table. Then SYSOL applies the gain and weight corrections. See § 4.1.1 and § 4.3.15.

O.1.8.1 Reading solar data from the VLA archive

To load a solar *uv*-data file to disk from an old VLA archive data set follow the general instructions given above (§ O.1.1 and § O.1.2) with the following additions:

> VLAMODE 'S ' C_R	to indicate solar mode observing.
> CPARM(2) 16 C_R	to indicate that moving sources are allowed without renaming.

If your experiment involved observing active solar phenomena, (*e.g.*, flares), you may wish to update the system-temperature correction every integration time. For example, if you observed a flare with an integration time $\tau = 1.67$ seconds, choose

> CPARM(8) 1.67 / 60 C_R	for 1.67 sec CL and TY table intervals.

Loading an entire solar *uv*-data set to disk with the minimum integration time results in large disk files which make all subsequent programs take a longer time to run. By modern standards, historic VLA data sets are relatively small, so the following may no longer be necessary. A useful strategy is to load the data with relatively low time resolution (20–30 seconds for observations of active solar phenomena) and to proceed with the usual continuum data calibration, deferring the system temperature correction. When a

satisfactory calibration is obtained, the relevant SN table may be saved using TASAV. (Note that you must save the SN table, before running CLCAL rather than the final CL table.) Then run CLCAL and inspect the data for interesting periods of activity — try UVPLT with BPARM = 11, 1 for plots of amplitude versus time or TVFLG, displaying amplitudes as a function of baseline length and time. Use FILLM to load the relevant time ranges of solar *uv* data to disk with no averaging. The saved SN table is then copied to each high-time resolution data set. Assess, and possibly edit, the nominal sensitivities (§ O.1.8.2) and then apply the system-temperature corrections (§ O.1.8.3). Finally, apply the saved/copied SN table to the CL table of each using CLCAL.

O.1.8.2 Using SNPLT and LISTR to assess the nominal sensitivities

When solar *uv* data are written to disk, FILLM writes the nominal sensitivities of those antennas equipped with solar CALs into the TY table. Before bootstrapping the system temperature correction for antennas without solar CALs from those which do, it is always wise to examine the nominal sensitivity for each of the solar CAL antennas for each of the IFs. The tools available for this purpose include: SNPLT, which plots the nominal sensitivities in graphical form, LISTR or PRTAB, which allow one to inspect the values directly, and EDITA, which provides an interactive display of the TY data and allows you to edit the data. To make plots:

> TASK 'SNPLT' ; INP C_R	to review the inputs needed.
> IND *m* ; GETN *n* C_R	to specify the input *uv* file.
> INEXT 'TY' C_R	to plot data from TY extension table.
> INVERS 0 C_R	to use the highest version number.
> SOURCES 'SUN' , ' ' C_R	to plot solar source only.
> TIMERANG 0 C_R	to select all times.
> ANTENNAS 5 11 12 18 C_R	to select only CAL-equipped antennas; this sample list for K, U, or C band.
> PIXRANGE 0 C_R	to self-scale each plot.
> NPLOTS 4 C_R	to do 4 plots on a page.
> FACTOR 2 ; SYMBOL 5 C_R	to use triangles to mark the data and enlarge them by a factor of 2. The symbols may even be connected by lines.
> XINC 1 C_R	to plot every XINC$^{\rm th}$ point.
> OPTYPE 'TSYS' C_R	to plot nominal sensitivities.
> INP C_R	to review the inputs.
> GO C_R	to run the program when you're satisfied with inputs.

SNPLT produces a PL extension file which may be plotted using LWPLA, TKPL, or TVPL — or you could set DOTV TRUE in SNPLT and get the display directly (and temporarily) on the TV. Then to inspect the values over some limited time range in detail, run LISTR (assuming the adverbs set above and):

> TASK 'LISTR' ; INP C_R	to review the inputs needed.
> OPTYPE 'GAIN' C_R	to list quantities in a calibration file.
> INEXT 'TY' C_R	to select the sensitivities.
> TIMER *d1 h1 m1 s1 d2 h2 m2 s2* C_R	to select by suspect time range.
> DOCRT -1 C_R	to route output to the printer.
> DPARM 10 0 C_R	to list nominal sensitivities.
> INP C_R	to review the inputs.
> GO C_R	to run the program when you're satisfied with inputs.

Task SNIFS is similar to SNPLT except that it plots IF on the x axis to compare solutions across them. It has numerous binning options to control the otherwise excessive plotting.

The use of EDITA with TY tables is described extensively in § 4.3.11 and need not be described further here.

O.1.8.3 Using SOLCL to apply the system-temperature correction

For the old VLA, once you have identified the appropriate subset of reference solar CAL antennas for each source and IF, you are ready to bootstrap the system-temperature correction of the remaining antennas. It is recommended that you run SOLCL before applying any other calibration to the CL table. In this way, you can easily verify that the appropriate corrections have been made to each antenna. Then you apply the system-temperature correction to version 2 and correct mistakes by deleting and recreating version 2. To run SOLCL:

> TASK 'SOLCL' ; INP C_R	to review the inputs needed.
> SOURCES '*' C_R	to correct all sources.
> STOKES ' ' C_R	to correct both polarizations.
> TIMERANG 0 C_R	to correct all times.
> ANTENNAS 5 11 12 18 C_R	to use the listed antennas as references.
> SUBARRAY 1 C_R	to modify sub-array 1.
> GAINVER 2 C_R	to write corrected entries to CL table version 2.
> INP C_R	to review the inputs.
> GO C_R	to run the program when you're satisfied with inputs.

After applying the system temperature correction, you may proceed with the usual *AIPS* data calibration procedures outlined in previous sections, including the special solar tactics described in § O.1.8.1.

O.2 Old VLBI format data

For data from a MkIII correlator, run MK3TX, MK3IN, MSORT, DBCON, UVAVG, TAMRG, SBCOR, and INDXR as needed (§ O.2.1.1–§ O.2.1.7). However, observations which require multiple passes through the correlator (including MkIII Modes A, B, and C observations) will have one file per observing mode *per correlation pass*. Data from separate correlator passes can be concatenated using task VBGLU and/or merged with task VBMRG.

O.2.1 Loading data from a MkIII/MkIV correlator

O.2.1.1 Running MK3IN

Data from a MkIII correlator, such as that in Bonn, Germany or Haystack, Massachusetts, can also be read into *AIPS*. To do this you need to be supplied with the so called "A" tape output, also known as "type 52's." These data tapes can be read and translated by the task MK3IN. The process of reading MkIII correlator data into *AIPS* and preparing it for further processing is more cumbersome than the equivalent process for VLBA correlator data. This simply reflects the manner in which data are generated on a baseline-based correlator with a limited number of playback drives. MkIII data may also appear in the form of a Unix tar file. For such data, use M3TAR and TFILE rather than MK3IN and AFILE, respectively.

Before running MK3IN, run the task MK3TX to extract the text files from the MkIII archive tape. These text files contain information about the correlated scans in the data set. MK3TX will first provide an index of all the text files and then ask you to select files for loading onto disk. It then asks you interactively for the desired

destination of the text files. It is important to load and concatenate all the "A" files, *i.e.*, those files having names like A*tttt*. The meaning of the other text files is described in the MK3TX Explain file. Sometimes the text files are not on the tapes, which means that you cannot select sub-sets of the data using the A-files, but is not otherwise catastrophic.

If the A-files are present and have been loaded onto the disk, use AFILE to sort and edit these files to produce a list of scans to be loaded by MK3IN. Use APARM settings in AFILE to establish criteria for selecting between any duplicate scans which may appear on the archive. If the data set contains data at multiple frequencies, you should edit the resulting output text file so that there is a version for each frequency, containing only those scans at that frequency.

The final step before running MK3IN is to create another text file which provides the commands for the task. This step is necessary since some information that is needed by *AIPS* is not present on the tape. Ideally, in this text file (as shown below), the parameter STATIONS should be a list of all the stations correlated, with the exact name used at correlation. If you do not have such a list, you can instead specify a list containing STATIONS 'ANY', 'ANY' ... Note that there must be at least as many 'ANY' entries as there are stations in the data set or some of the stations will not be loaded. The parameters in this text file are:

STOKES='RR','LL'	the Stokes range of the output file. The standard abbreviations are used to select the polarization range. The largest consistent range is used. For example: STOKES='RR','LL' will cause only RR and LL to be written. STOKES='LL' will cause just LL to be written. STOKES='RR','LR' will cause all four circular polarization combinations to be in the output file, since RR and LR span the range of allowed *AIPS* Stokes values.
FREQCODE='R','L','r','l'	the polarization codes used by MkIII correlators are anything but standard and they need to be supplied to MK3IN using the parameter FREQCODE. The one character polarization identifiers are expected in the order RR, LL, RL, and LR. The usual correlator convention is 'R'=RR, 'L'=LL, 'r'=RL, 'l'=LR and this is the default assumed by MK3IN. However, other codes are possible. For example FREQCODE = 'A', 'B', 'C', 'D' will interpret 'A' as RR, 'B' as LL and so forth, while FREQCODE = 'R', 'C', 'r', 'l' will use the default abbreviations except that 'C'=LL. If MK3IN encounters an unidentified polarization code the task will report: AT20XX: Unidentified Stokes parameter: '*X*'. In this case, modify the FREQCODE parameter to include this polarization identifier. This will ensure that polarizations are not misidentified inadvertently.
NO_POL=2	the number of polarization correlations (*e.g.*, RR, LL, RL and LR), the default is 1.
STATIONS='NRAO','VLA','OVRO','FDVS','MPI'	station names.
/	keyin style delimiter.

Then, from inside AIPS, mount the tape (§ 3.9) and run MK3IN:

> TASK 'MK3IN' ; INP C$_R$	to review the inputs.
> INFILE 'MYVLB:PARAM.LIS' C$_R$	to define the text control file.
> IN2FILE 'MYVLB:AFILE.LIS C$_R$	to point to a file containing a list of scans to be loaded as produced by AFILE
> INTAPE 4 C$_R$	to specify the tape drive number.
> NFILES 0 C$_R$	to skip no files on tape.

> OUTNA 'EXP 86-34' C$_R$	to select the output file name.
> OUTCL 'MK3IN' C$_R$	to select the default output class name.
> REFDATE '12/11/89' C$_R$	to tell MK3IN the start date of the observations — get this right or you may get negative times.
> SOURCES '' C$_R$	to accept all sources found.
> TIMERANG 0 C$_R$	to accept data from all times found.
> DOUVCOMP 1 C$_R$	to write data on disk in compressed format.
> APARM 1, 0 C$_R$	to set the time increment in the CL table entries in minutes.
> APARM(7) 1 C$_R$	to separate sidebands into separate *AIPS* IFs; the default is to store both USB and LSB in the same IF.
> GO C$_R$	to run the program.

If the data are contained on more than one Exabyte or DAT tape, load the second tape and re-run MK3IN, setting DOCONCAT = 1 C$_R$ so that the data are appended to the previous output file. Before running MK3IN a second time, it is important to set the list of STATIONS in the control file to exactly those found when loading the first tape; use PRTAN on the output file to obtain this list. Also leave additional 'ANY' entries after the list for any stations that are on the second tape but which were not on the first tape. The use of DOUVCOMP = 1 is recommended for most data sets, see Appendix F.

O.2.1.2 Sorting MkIII/IV data

The *AIPS* data files created by MK3IN will be in an arbitrary sort order. Use UVSRT or MSORT to sort them into time-baseline order:

> TASK 'UVSRT' ; INP C$_R$	to review the inputs.
> INDISK *n* ; GETN *ctn* C$_R$	to select the input file.
> OUTNA INNA ; OUTCL 'TBSRT' C$_R$	to specify the output file.
> SORT 'TB' C$_R$	to sort to time-baseline order.
> GO C$_R$	to make the sorted *uv* file.

O.2.1.3 Concatenating MkIII/IV data

If you did not set DOCONCAT=1 when running MK3IN and as a result several files were loaded from tape for one observation, use DBCON to concatenate them together. In order to have the concatenated data all appear in a single subarray, both input files for DBCON must have the same reference day number and identical antenna numbers. That is, the antennas extension (AN) files with each input *uv* data file must be the same. MATCH may be used to repair discrepancies.

You may list the contents of AN files using PRTAN. To run DBCON:

> TASK 'DBCON' ; INP C$_R$	to review the inputs.
> INDISK *n1* ; GETN *ctn1* C$_R$	to select the 1st input file.
> IN2DISK *n2* ; GET2N *ctn2* C$_R$	to select the 2nd input file.
> OUTNA INNA ; OUTCL 'DBCON' C$_R$	to specify the output file.
> DOARRAY 1 C$_R$	to force DBCON to mark the output data records as being in the same sub-array. For this to work properly, both of the input files must have the same reference day and have identical antennas files.
> GO C$_R$	to concatenate the two files.

Task DBAPP may be used to avoid the 2^n proliferation of files, but only if the files are fairly similar in antennas, subarrays, and frequency IDs.

O.2.1.4 Labeling correlator polarization data

Most MkIII and MkIV VLBI setups reverse the polarizations and assign odd-numbered bands to LCP and even-numbered bands to RCP. In this case BANDPOL should be set to '*(LR) ' and the output data set will again be of equal size to the input data with two polarizations and half the number of IFs. This case normally applies if LISTR shows pairs of IFs with the same frequency and QHEADER shows one pixel on the STOKES axis with coordinate value LL, but there may be exceptions to this rule when non-VLBA antennas are used.

To use FXPOL directly, typical inputs are:

> TASK 'FXPOL' ; INP ↵	to review the inputs.
> INDISK *n* ; GETN *ctn* ↵	to specify the input file.
> BANDPOL '*(LR)' ↵	to specify the normal MkIII and MkIV polarization structure.
> GO ↵	to run the program.

Consult HELP FXPOL for further information about more complicated cases. Note that FXPOL has to write a new output file since the structure of the data is being changed. All standard extension files are also converted, but it is still a good idea to run FXPOL before running the calibration tasks.

O.2.1.5 Merging MkIII/IV data

MkIII VLBI correlators usually produce redundantly correlated data. You must merge the data using UVAVG:

> TASK 'UVAVG' ; INP ↵	to review the inputs.
> INDISK *n* ; GETN *ctn* ↵	to specify the input file.
> OUTNA INNA ; OUTCL 'UVMRG' ↵	to specify the output file.
> YINC 4.0 ↵	to set the averaging interval of the input data records (in seconds).
> OPCODE 'MERG' ↵	to direct the task to perform the merge operation.
> GO ↵	to run the program.

The CL table should only contain one entry for each antenna at each time stamp. But, due to the merging process described above and the fact that redundant correlations may have been performed, there is one step to follow before you have consolidated your database fully. You must run TAMRG to remove the redundant CL entries:

> TASK 'TAMRG' ; INP ↵	to review the inputs.
> INDISK *n* ; GETN *ctn* ↵	to specify the input file.
> INEXT 'CL' ↵	to specify the table type to merge.
> INVER 1; OUTVER INVER ↵	to process the input table in place.
> APARM 4, 1, 4, 0, 1, 1, 1, 0 ↵	to control the merging: don't ask why, just do it!
> BPARM 1, 4 ↵	to set compared columns — again, don't ask.
> CPARM 1.157e-5, 0.2 ↵	to set degree of equality — ditto.
> GO ↵	to run the program.

O.2.1.6 Correcting MkIII/IV sideband phase offsets

If your observation contains a mixture of VLBA and non-VLBA antennas and you have not stored the sidebands as separate IFs, there will be a phase offset of about 130° between the upper and lower sidebands on baselines from VLBA to non-VLBA antennas. A correction for this offset is achieved using the task SBCOR:

> TASK 'SBCOR' ; INP ↵	to review the inputs.
> INDISK *n1* ; GETN *ctn* ↵	to specify the input file.
> OUTNA INNA ; OUTCL 'SBCOR' ↵	to specify the output file.
> BCHAN 1 ↵	to specify the lowest channel of lower sideband.
> ECHAN 4 ↵	to specify the highest channel of lower sideband.
> APARM(1) 0 ↵	to apply the default phase offset (*i.e.*, $-130^{\rm deg}$.)
> ANTENNAS = VLBA ; INP ↵	to specify the VLBA antenna numbers; the = sign is required here. The verb VLBA reads the antenna file to find VLBA antennas.
> GO ↵	to run the program.

If you have loaded the VLBAUTIL procedures, then you may use a procedure called ANTNUM to translate a station name into a station number. Thus ANTENNAS = ANTNUM('BR'), ANTNUM('FD'), ... The verb VLBA in is easier.

O.2.1.7 Indexing MkIII/IV data

Next, you must index your data. The NX table is useful as a summary of the file for you, and is also used by the calibration programs to provide quick access for reading data. Create this file with INDXR:

> TASK 'INDXR' ; INP ↵	to review the inputs.
> INDISK *n* ; GETN *ctn* ↵	to specify the input file.
> CPARM 0, 30, -1 ↵	to allow ≤ 10-minute time gaps within scans, to limit scans to ≤ 30 minutes, and to not create a new CL table.
> GO ↵	to run the program.

Files with suffixes .SCAN and .MKIII contain scan summaries and MkIII information and are for information purposes only.

Other than these initial loading and merging steps, the reduction of MkIII and MkIV correlator data is identical to that of VLBA correlator data.

For MkIII data from the Bonn correlator, phase-cal measurements are incorporated directly into the first CL table produced by MK3IN — this is another strong reason to protect the first CL table.